

# iVIEW Suite

Version 5.7



## Troubleshooting Guide

## NOTICE

© 2000-2008 RADVISION Ltd. All intellectual property rights in this publication are owned by RADVISION Ltd and are protected by United States copyright laws, other applicable copyright laws and international treaty provisions. RADVISION Ltd retains all rights not expressly granted.

This publication is RADVISION confidential. No part of this publication may be reproduced in any form whatsoever or used to make any derivative work without prior written approval by RADVISION Ltd.

No representation of warranties for fitness for any purpose other than what is specifically mentioned in this guide is made either by RADVISION Ltd or its agents.

RADVISION Ltd reserves the right to revise this publication and make changes without obligation to notify any person of such revisions or changes. RADVISION Ltd may make improvements or changes in the product(s) and/or the program(s) described in this documentation at any time.

If there is any software on removable media described in this publication, it is furnished under a license agreement included with the product as a separate document. If you are unable to locate a copy, please contact RADVISION Ltd and a copy will be provided to you.

Unless otherwise indicated, RADVISION registered trademarks are registered in the United States and other territories. All registered trademarks recognized.

GoAhead WebServer is used by permission from GoAhead Software, Inc. GoAhead WebServer is used by permission from GoAhead Software, Inc. Copyright © 2006 GoAhead Software, Inc. All Rights Reserved.

For further information contact RADVISION or your local distributor or reseller.

iVIEW Suite version 5.7, June 2008

Publication 1

<http://www.radvision.com>

# CONTENTS

---

## *About This Manual*

Related Documentation	v
Feedback	v

## *Troubleshooting*

How to Resolve Browser Authentication Issues	2
Recognizing a Local Intranet Site	2
Enabling Single Sign-on	2
Configuring Outlook Add-on for Single Sign-on	2
How to Resolve iCM Microsoft Outlook Add-on Configuration Issues	3
Connecting the iCM Microsoft Outlook Add-on to iCM	3
Disabling Pop-up Messages	3
How to Resolve User Experience Issues	4
Enabling Internet Explorer Pop-up Blocker	4
Navigating Between Pages	4
Configuring Maximum Time Period for Recurring Meetings	4
Correcting Web Page and Pop-up Window Display	4
How to Resolve Administration Issues	5
Database Unavailable	5
Using Double-Byte Characters in the MCU Service Template	5
Configuring Terminal Area Codes	5
Assigning DID Numbers	5
Resolving a Port Conflict	6
Resolving a Scheduling Failure	6
Resolving a Failed Terminal Invitation	8
Resolving a Meeting Creation Failure	9



# ABOUT THIS MANUAL

---

The [iVIEW Suite Troubleshooting Guide](#) provides information for administrators about iVIEW Suite installation, configuration and the user interface. It includes detailed procedures about performing administrator-related tasks.

## RELATED DOCUMENTATION

The iVIEW Suite documentation set is available on the RADVISION Utilities and Documentation CD-ROM supplied with the product and includes manuals and online helps. The manuals are in PDF format.

---

**Note** You require Adobe Acrobat Reader version 5.0 or later to open the PDF files. You can download Acrobat Reader free of charge from [www.adobe.com](http://www.adobe.com).

---

## FEEDBACK

The team at RADVISION constantly endeavors to provide accurate and informative documentation. If you have comments or suggestions regarding improvements to future publications, we would value your feedback.

Please send your comments to [doc\\_comments@radvision.com](mailto:doc_comments@radvision.com).

We thank you for your contribution.



# TROUBLESHOOTING

---

- [How to Resolve Browser Authentication Issues](#) on page 2
- [How to Resolve iCM Microsoft Outlook Add-on Configuration Issues](#) on page 3
- [How to Resolve User Experience Issues](#) on page 4
- [How to Resolve Administration Issues](#) on page 5
- [Resolving a Port Conflict](#) on page 6
- [Resolving a Scheduling Failure](#) on page 6
- [Resolving a Failed Terminal Invitation](#) on page 8
- [Resolving a Meeting Creation Failure](#) on page 9

## HOW TO RESOLVE BROWSER AUTHENTICATION ISSUES

- [Recognizing a Local Intranet Site](#) on page 2
- [Enabling Single Sign-on](#) on page 2
- [Configuring Outlook Add-on for Single Sign-on](#) on page 2

### RECOGNIZING A LOCAL INTRANET SITE

#### Symptom

The browser does not recognize iCM as a local Intranet site and an authentication window appears.

#### Recommended Action

- Provide users with a link to iVIEW Suite that includes the necessary fully qualified domain name (FDQN), rather than only the iCM IP address.
- Configure the browser for the user so that iCM is a local Intranet site.

### ENABLING SINGLE SIGN-ON

#### Symptom

iVIEW Suite web pages always require that you enter a user name and password.

#### Recommended Action

Use Single Sign-on (SSO). SSO enables users to access iVIEW Suite web pages without having to enter a user name or password. Users are authenticated transparently using domain account and password credentials.

To enable Single Sign-on, during installation choose the **Single Sign-on** check box. You must also add the iVIEW Suite host server to the trusted site of the client browser.

### CONFIGURING OUTLOOK ADD-ON FOR SINGLE SIGN-ON

#### Symptom

iCM authentication fails when working with SSO and iCM Microsoft Outlook Add-on.

#### Recommended Action

Go to **Tools > Options > iVIEW Suite Meetings**. In the Outlook options, make sure the User ID, Password, and Organization fields are blank.

iCM automatically performs authentication using the domain account/password credentials.

## HOW TO RESOLVE ICM MICROSOFT OUTLOOK ADD-ON CONFIGURATION ISSUES

- [Connecting the iCM Microsoft Outlook Add-on to iCM](#) on page 3
- [Disabling Pop-up Messages](#) on page 3

### CONNECTING THE ICM MICROSOFT OUTLOOK ADD-ON TO ICM

#### Symptom

The iCM Microsoft Outlook Add-on fails to connect to iCM.

#### Recommended Action

After installing the iCM Microsoft Outlook Add-on, go to **Tools > Options > iVIEW Suite Meetings** and enter the URL of your server in the Web Site field.

### DISABLING POP-UP MESSAGES

#### Symptom

The standard Microsoft Outlook 2003 pop-up message warning that another application is trying to access Outlook information appears.

#### Recommended Action

Use the new registry key

**HKEY\_CURRENT\_USER\Software\Policies\Microsoft\Security\CheckAdminSettings**

for the Outlook client machine, and then set the value to 1.

---

**Note** To disable the pop-up message from the exchange-server side, refer to Microsoft documentation.

---

Meetings scheduled from iCM Microsoft Outlook Add-on, use the meeting organizer time zone setting from iVIEW Suite. Time zone settings on the work station of a Meeting Organizer should match the settings in iVIEW Suite. You can change time zone settings in iCM in My Profile.

---

**Note** RADVISION recommends that meetings created via the iCM Microsoft Outlook Add-on contain no more than 100 participants.

---

## HOW TO RESOLVE USER EXPERIENCE ISSUES

- [Enabling Internet Explorer Pop-up Blocker](#) on page 4
- [Navigating Between Pages](#) on page 4
- [Configuring Maximum Time Period for Recurring Meetings](#) on page 4
- [Correcting Web Page and Pop-up Window Display](#) on page 4

### ENABLING INTERNET EXPLORER POP-UP BLOCKER

#### Symptom

Internet Explorer Pop-up Blocker is inactive.

#### Recommended Action

If you are using Microsoft Windows XP SP2 or Windows 2003 Service Pack 1, to enable Internet Explorer Pop-up Blocker, add the iCM site to the list of allowed sites. To do this, go to **Tools > Internet Options > Privacy > Pop-up Blocker Settings**, and then add the iCM site.

### NAVIGATING BETWEEN PAGES

#### Symptom

Internet Explorer browser navigation buttons (Back, Forward and Refresh) do not work correctly in the iVIEW Suite user interface.

#### Recommended Action

Use the **Next** and **Back** buttons in iVIEW Suite to navigate between pages.

### CONFIGURING MAXIMUM TIME PERIOD FOR RECURRING MEETINGS

#### Symptom

You want to schedule recurring meetings for a period longer than that allowed in the iVIEW Suite Web user interface.

#### Recommended Action

Use the iCM Configuration Tool to schedule recurring meetings for up to 730 days.

### CORRECTING WEB PAGE AND POP-UP WINDOW DISPLAY

#### Symptom

Some Web pages and pop-up windows do not display normally.

#### Recommended Action

Set the screen resolution to a standard resolution such as 800 x 600 pixels or 1024 x 768 pixels. The minimum recommended resolution is 800 x 600 pixels and the recommended font size is Normal or Large.

## HOW TO RESOLVE ADMINISTRATION ISSUES

- [Database Unavailable](#) on page 5
- [Using Double-Byte Characters in the MCU Service Template](#) on page 5
- [Configuring Terminal Area Codes](#) on page 5
- [Assigning DID Numbers](#) on page 5

### DATABASE UNAVAILABLE

#### Symptom

No database is available when iVIEW Suite is initially started.

#### Recommended Action

Restart the service when the database is ready.

If the connection between the database and iVIEW Suite is lost after initially starting iVIEW Suite, iVIEW Suite works normally when the database is operating.

### USING DOUBLE-BYTE CHARACTERS IN THE MCU SERVICE TEMPLATE

#### Symptom

Unicode and other double-byte characters (such as Chinese, Japanese, Korean, and Hebrew characters) cause device exception in MCU service template Name, Description, Terminal Name and Gateway Service Prefix fields.

#### Recommended Action

Use only ASCII text in these fields.

### CONFIGURING TERMINAL AREA CODES

#### Symptom

Terminal area codes are incorrectly defined.

#### Recommended Action

Do not include domestic long-distance prefixes in terminal area codes.

### ASSIGNING DID NUMBERS

#### Symptom

Cannot change Direct Inward Dialing (DID) numbers

#### Recommended Action

DID numbers are assigned on a per-endpoint basis rather than on a per-meeting basis. This is an internal configuration that cannot be changed via the Configuration Tool or the iVIEW Suite Web interface. To manually change the host name, perform the following procedure.



### Procedure

- 1 Go to  
C:\Program Files\RADVISION\iVIEW Suite\iCM\jboss-3.2.5\bin  
where C is the local drive.
  - 2 Make a backup copy of the vcs-config.xml file.
  - 3 Open the vcs-config.xml file with a text editing tool and modify the  
<host-url> element to the required value.
  - 4 Save the file in the text editor.
  - 5 Restart iVIEW Suite.
- 

## RESOLVING A PORT CONFLICT

### Symptom

A port conflict occurs when you try to install or run certain applications.

### Recommended Action

Ensure that ports 1098 and 1099 are free. Run the “netstat” command in the DOS window to determine which applications (if any) occupy ports 1098 and 1099.

## RESOLVING A SCHEDULING FAILURE

### Symptom

In iCM, in My Meetings or All Meetings, on the Current tab, if Failed appears, if you click Failed, the message that opens reads: “Unable to create the meeting as scheduled. Please check your meeting settings.”

### Recommended Action

A scheduling failure may occur if a meeting type is downloaded, and then the meeting type is changed on the MCU but the iCM does not update the meeting types.



### Procedure

- 1 To confirm that the reason for the failure is an incompatible meeting type, select **Admin > Meeting Types** and click **Download**.
- 2 If the meeting type that you specified appears in the Meeting Types (Service) Conflicts list, the reason for the scheduling failure is, at least in part, an incompatible meeting type.

---

**Note** If a meeting is created even though the specified meeting type is incompatible, there may be resource-calculation errors.

---

- 3 To resolve the conflict, repeat the download of the meeting type you require.
- 

### Recommended Action

If actual MCU resources are changed after the MCU is added in iCM but iCM does not update or synchronize the actual MCU information, then the result may be an incompatible MCU.



### Procedure

- 1 To determine which MCU is actually assigned to the meeting, select **Admin > All Meetings**.
- 2 Click the required MCU in the **MCU** column on the **Current** tab.
- 3 In the Modify MCU window, click **Synchronize**.  
The MCU profile is updated.
- 4 Make sure the MCU registered gatekeeper is configured correctly.
- 5 Make sure the connection configuration in **Admin > Network Management > IP Topology** is correct.

---

**Note** The Network Management section is hidden by default in iCM. Use the iCMConfiguration Tool to change default settings in the user-interface.

---

## RESOLVING A FAILED TERMINAL INVITATION

### Symptom

You are not able to invite a terminal to a meeting.

### Possible Cause

Incompatible gatekeeper registration. The MCU may be registered to a gatekeeper that is different than the one specified in the MCU profile in iCM.

### Recommended Action



### Procedure

- 1 In the **MCU** section of the SCOPIA MCU application, check that the ECS that is listed is the same as the one designated in iCM.
  - 2 If the gatekeeper is not the same, then in iCM, select the same gatekeeper to which the MCU is registered.
- 

### Possible Cause

Authorization failure. ECS version 4.1.5.0 or later allows multiple iCM to connect as authorizer. However, if multiple iCM authorizes a single ECS, the iCM/ECS authorization logic does not work.

### Recommended Action

Ensure that each ECS has only one iCM as its authorizer. If multiple iCM authorizes a single ECS, remove all other iCM authorization connections, and then restart ECS. Only after this does the remaining iCM work with this ECS properly in authorization mode.

---

**Note** iCM initiates the authorization connection to the ECS. Ensure that the ECS server SNMP Community names are set correctly in the iCM user interface.

---

### Possible Cause

Unconnected IP location (at Network Management > IP Topology) for the MCU and a terminal.

If a meeting is set up on the MCU that belongs to a specific location defined at Network Management > IP Topology, a terminal is invited to a different location, the location to which the MCU is assigned may not be able to connect to the location to which the terminal is assigned.

### Recommended Action



#### Procedure

- 1 In iCM, on the IP Topology tab, check that there is a link between the two different locations.
- 2 Make sure that if there is a connection, that Bandwidth and Location are correctly defined.
- 3 Alternatively, assign the MCU and the terminal to the same location.
- 4 Make sure that the gatekeeper that the terminal is assigned to is in Authorization Mode.

---

**Note** Cascading is set up in iCM in the Network Management section, on the IP Topology tab. If the IP Topology tab is hidden, in the iCM Configuration Tool, in System Configuration > UI Settings, check **IP Topology** to activate the IP Topology tab.

---

## RESOLVING A MEETING CREATION FAILURE

### Symptom

A meeting is successfully scheduled but cannot actually be created.

### Recommended Action



#### Procedure

- 1 Make a point-to-point call.
- 2 Ensure that the call is successful from within iCM. A successful point-to-point call indicates that the ECS and iCM are configured correctly.
- 3 Create an endpoint-initiated MCU conference. If the endpoint connects, the MCU, ECS and iCM are configured properly.

## Resolving a Meeting Creation Failure

- 4 Schedule a meeting in iCM. If the meeting is scheduled successfully, wait for the meeting to start. If the meeting starts successfully, dial into the meeting using an endpoint.
- 

### Recommended Action

In the event that the troubleshooting procedures in this section do not resolve a meeting creation or meeting invitation issue, use the procedure in this section.



### Procedure

- 1 Attempt the same meeting creation or invitation directly on the MCU without using the iCM.
  - 2 If the same meeting creation or invitation does not succeed directly on the MCU, restart the MCU.
  - 3 If restarting the MCU does not resolve the issue, contact your MCU service representative.
-